























Упрощение логической функции. Карты Карно


Упростить логическую функцию, заданную картой Карно.




Задача 32.22. 9




Задача 32.23. 9




Задача 32.24. 9




Задача 32.25. 9




Задача 32.26. 9




Задача 32.27. 9




Задача 32.28. 9




Задача 32.29. 9




Задача 32.30. 9




Задача 32.31. 9




Задача 32.32. 9



Задача 32.33. 9



Задача 32.34. 9



Упрощение логической функции. Карты Карно

1	$wy \vee \bar{x}w$	0 1 0 1 0 1 0 1 0 0 0 0 0 1 0 1
2	$\bar{z}\bar{x}\bar{y} \vee \bar{w}x \vee \bar{w}y$	1 1 0 0 1 0 1 0 1 0 1 0 1 0 1 0
3	$\bar{x}wy \vee \bar{y}x$	0 0 0 0 0 1 0 1 1 1 1 1 0 0 0 0
4	$\bar{x}y \vee z\bar{w}$	0 0 1 0 1 1 1 1 0 0 1 0 0 0 1 0
5	$w\bar{x}\bar{y}z \vee yx$	0 0 0 1 0 0 0 0 0 0 0 0 0 1 1 1
6	$zy \vee \bar{z}\bar{x}\bar{w}\bar{y}$	1 0 0 0 0 0 1 1 0 0 0 0 0 0 1 1
7	$\bar{y}w\bar{x} \vee ywz \vee y\bar{w}\bar{x} \vee \bar{y}\bar{w}xz$	0 1 0 1 1 0 1 1 0 0 1 0 0 0 0 1
8	$\bar{z}x \vee zy$	0 0 0 0 0 0 1 1 1 1 0 0 1 1 1 1
9	$\bar{z}\bar{x}\bar{w} \vee \bar{y}x \vee \bar{y}w$	1 1 0 1 1 0 0 0 1 1 1 1 0 0 0 0
10	$x\bar{y} \vee yzw\bar{x}$	0 0 0 0 0 0 0 1 1 1 1 1 0 0 0 0
11	$\bar{w}x \vee wz$	0 0 0 1 0 0 0 1 1 0 1 1 1 0 1 1
12	$zw \vee \bar{y}z$	0 0 1 1 0 0 0 1 0 0 1 1 0 0 0 1
13	$\bar{w}z \vee w\bar{z}y \vee \bar{w}x\bar{y}$	0 0 1 0 0 1 1 0 1 0 1 0 0 1 1 0
14	$x\bar{w}\bar{y}z \vee yw$	0 0 0 0 0 1 0 1 0 0 1 0 0 1 0 1
15	$\bar{z}wx \vee \bar{x}z$	0 0 1 1 0 0 1 1 0 1 0 0 0 1 0 0
16	$z\bar{w} \vee wxy\bar{z}$	0 0 1 0 0 0 1 0 0 0 1 0 0 1 1 0
17	$\bar{x}w \vee xz$	0 1 0 1 0 1 0 1 0 0 1 1 0 0 1 1
18	$xw \vee \bar{x}\bar{y}\bar{z}\bar{w}$	1 0 0 0 0 0 0 0 0 1 0 1 0 1 0 1
19	$\bar{z}\bar{y}\bar{w} \vee \bar{x}z\bar{y} \vee xzyw$	1 0 1 1 0 0 0 0 1 0 0 0 0 0 0 1
20	$\bar{w}\bar{z} \vee yx$	1 0 0 0 1 0 0 0 1 0 0 0 1 1 1 1
21	$\bar{w}yz \vee z\bar{x} \vee w\bar{y}$	0 1 1 1 0 0 1 1 0 1 0 1 0 0 1 0
22	$\bar{y}\bar{z}\bar{w} \vee \bar{x}z \vee \bar{x}w$	1 1 1 1 0 1 1 1 1 0 0 0 0 0 0 0
23	$\bar{w}z \vee wy$	0 0 1 0 0 1 1 1 0 0 1 0 0 1 1 1
24	$\bar{y}z \vee x\bar{w}$	0 0 1 1 0 0 0 0 1 0 1 1 1 0 1 0
25	$w\bar{z}\bar{x}y \vee xz$	0 0 0 0 0 1 0 0 0 0 1 1 0 0 1 1
26	$\bar{w}z \vee wy$	0 0 1 0 0 1 1 1 0 0 1 0 0 1 1 1
27	$\bar{z}wx \vee z\bar{x}\bar{y} \vee \bar{x}zw$	0 0 1 1 0 0 0 1 0 1 0 0 0 1 0 0
28	$\bar{w}z\bar{y} \vee wzx \vee w\bar{z}\bar{y} \vee \bar{w}\bar{z}y\bar{x}$	0 1 1 0 1 0 0 0 0 1 1 1 0 0 0 1
29	$\bar{z}\bar{w} \vee yx$	1 0 0 0 1 0 0 0 1 0 0 0 1 1 1 1
30	$\bar{y}z \vee x\bar{w}$	0 0 1 1 0 0 0 0 1 0 1 1 1 0 1 0
31	$x\bar{w} \vee wyz\bar{x}$	0 0 0 0 0 0 0 1 1 0 1 0 1 0 1 0
32	$\bar{x}z \vee y\bar{w}$	0 0 1 1 1 0 1 1 0 0 0 0 1 0 1 0
33	$\bar{w}y\bar{z} \vee wyx \vee w\bar{y}\bar{z}$	0 1 0 0 1 0 0 0 0 1 0 0 1 1 0 1
34	$\bar{w}x \vee z\bar{y}$	0 0 1 1 0 0 0 0 1 0 1 1 1 0 1 0